


Internal RAM Clear Procedure



TEST POINT IS LABELED JP7 ON
BOARD VERSIONS 4 AND UP

TEST POINT IS LABELED JP5 ON
BOARD VERSIONS 3 AND BELOW

METAL TAB
GROUND

- 1) Power off the XC-6000 / 30B
- 2) Board version will dictate actual test point label. Both JP7 and JP5 are in the same physical location on the board.
- 3) Using a piece of wire making contact between the test point and ground, now power up the XC-6000 / 30B while still making connection between the test point and ground.
- 4) The 5 front LED's on XC-6000 / 30B should all come on and stay lit for 3-5 seconds. This is a good indication that the internal memory has cleared.